

N I M

1 6 I N P U T - 2 C H

S u m A m p

(N005)



- ◎ Linear signal of 16 input is added and output from two NIM connectors.
 - ◎ Input impedance 50 Ω
Output impedance 50 Ω
 - ◎ RAIZU time <5nSec
 - ◎ output 0 ~ -2 V (40 mA)
- to, the negative input type of the correspondence.

It is the most suitable for the addition of the counter signal.

< Specifications >

Input

Connector	:	LEMO
Impedance	:	50 Ω
Input range	:	0 V ~ -2 V

Output

Connector	:	LEMO
Polarity	:	The same polarity to the input
Output range	:	0 V ~ -2 V
Impedance	:	50 Ω
Delay	:	~ 5 n S e c
Form	:	NIM standard 1 width module
Power supply	:	+ 6 V 200 mA
		+ 12 V 100 mA
		- 6 V 200 mA
		- 12 V 300 mA